

# EB70

## Portable Power Station



1000W Power



100W USB-C



10 Outlets



4 Ways to  
Recharge



716Wh  
Capacity



2,500+  
Life Cycles



## Engineered for a Mobile Lifestyle



### Outdoor Adventure

From mobile phones and laptops to a variety of small appliances, the EB70 can power almost anything you need on the move, adding comfort and convenience to your camping and outdoor experience.



### Emergency Preparedness

During unexpected outages or emergencies, the EB70 delivers a trustworthy home backup solution to meet your essential needs, keeping you connected and prepared when it matters most.



### Remote Working

Experience uninterrupted productivity with the EB70 portable power station, a thoughtful companion for your work and business. With its reliable power supply, you can keep your devices fully charged for important meetings and impactful presentations.

## Power for All Your Essentials



~ **45 times**  
Cell phone 10Wh



~ **9 times**  
Laptop 65Wh



~ **9 hrs**  
Car Refrigerator 60W



~ **45 hrs**  
LED Light 10W



~ **32 times**  
Camera 15W



~ **13 times**  
Drone 40Wh



~ **18 hrs**  
Fan 30W



~ **67 Minutes**  
Coffee Maker 500W

## BLUETTI EB70

### • Specifications

|                         |                     |
|-------------------------|---------------------|
| Model                   | EB70                |
| Battery Capacity        | 716Wh               |
| Battery Type            | LiFePO <sub>4</sub> |
| AC Output               | 1,000 W             |
| Net Weight              | 21.4LB/9.7KG        |
| Dimensions (L x W x H)  | 320 x 216 x 221 mm  |
| Charging Temperature    | 0°C -40°C           |
| Discharging Temperature | -20°C -40°C         |
| Storage Temperature     | -20°C -45°C         |

### • Input

|             |                                                 |
|-------------|-------------------------------------------------|
| AC Input    | 200W Max.                                       |
| Solar Input | 200W Max., 12V-28VDC, 8A Max.                   |
| Car Input   | 12V / 24V from Vehicle's Cigarette Lighter Port |

### • Output

|               |                        |
|---------------|------------------------|
| 2 x 220V-240V | AC Outlet              |
| 1 x 12V / 10A | Cigarette Lighter Port |
| 2 x 12V / 10A | DC5521 Port            |
| 2 x 15W Max.  | USB-A                  |
| 2 x 100W Max. | USB-C                  |
| 1 x 15W Max.  | Wireless Charging      |



### POWEROAK GMBH

LISE-MEITNER-STRASSE 14, 28816 STUHR, GERMANY  
SALE-DE@BLUETTIPOWER.COM TEL: +49 151 10622908

### BLUETTI ENERGY FRANCE SARL

SALES.FR@BLUETTI.COM TEL: +33 0784711486

### BLUETTI ENERGY ITALY SRL

GALLERIA DEL CORSO 1, 20122, MILANO, ITALY  
GALLERIA DEL CORSO 1, 20122, MILANO, ITALY  
JAMES@BLUETTI.COM TEL: +39 324 286 5555

### BLUETTI ENERGY SPAIN S.L

CALLE ALAJATE 3 2B MADRID SPAIN 28041  
ES@BLUETTI.COM TEL: 666189625

### BLUETTI ENERGY NETHERLANDS

KABELWEG 57, AMSTERDAM, THE NETHERLANDS  
SALES\_NL@BLUETTI.COM

### SHENZHEN POWEROAK NEWENER CO., LTD.

ADD: 19F, BLOCK A, KAIDAE BLDG., NO.168 TONGSHA RD.,  
NANSHAN DIST., SHENZHEN, GUANGDONG, CHINA