### BLUETTI



# **BLUETTI AC70P Portable Power Station**

**Designed to Up-level** Your Outdoor Experience



Elevate your on-the-go power solutions with the BLUETTI AC70P Power Station! Boasting a robust 864Wh capacity and a 1,000W continuous power, it effortlessly energizes your essential devices during outdoor adventures, RV escapades, or cozy moments at home. The lightweight and portable design ensures non-stop power is always at your service whenever you need.

864Wh	1,000W	2,000W
Capacity	Rated Power	Lifting Power
8	45	<45dB
Versatile Outlets	Minutes to 80%	Quiet Operation
5-Year	10.7kg	Арр
Warranty	Lightweight	Smart App Control
ALL THE REAL		
CERTIFICATION C		The second
	ROP BAR	

## Why Choose BLUETTI AC70P?

### Super-fast Charging For Minimal Downtime

With BLUETTI Turbo Charging Technology, you no longer have to wait a long time to get it charged. The fast charging allows you to replenish it at your last-minute pack-up, ensuring your power is at the ready before you hit the road.

#### Wall Charging



4 100% (1.5 Hours)

4100% (2.2 Hours)

Solar Charging (2.5x Faster than Previous Generation)

#### Up to 2,000W Lifting Power Power More High-powered Appliances

With a rated power of 1,000W, AC70P can handle 98% of outdoor and home appliances. It also features a Power Lifting Mode that boosts the power up to 2,000W, enabling it to run high-powered resistive loads effortlessly, such as electric grills, hairdryers, kettles, and more.



### Safe LiFePO<sub>4</sub> Battery & BMS Designed for 10 Years of Everyday Use

AC70P uses LiFePO4 battery cells, which have a natural advantage of remarkable thermal and chemical stability, giving you better performance and longer life cycle. The built-in intelligent BMS (Battery Management System) protects your devices from potential risks such as over voltage, over temperature, overload and short circuits.



#### 8 Versatile Ports Power for All Your Need

Flexible charging capability accommodates a wide range of charging needs. AC70P features 2 AC Outlets, 2 USB-A Ports, 2 USB-C Ports, 1 Cigarette Lighter Port, and 1 Wireless Charging Pad to charge multiple devices at the same time.



#### Multiple Charging Options Get Charged in Any Way You Like

AC70P gives you the freedom to recharge your devices in any way you prefer: wall charging, solar charging, car charging, generator charging, or LiFePO4 battery charging. Whether you are at home, on the road, or outdoors, you can always find a suitable power source for AC70P.







_	Ó	0	Ē	
Phone (11Wh)	Camera (16Wh)	Car Fridge (65W)	Toaster (650W)	Kettle (1,000W)
40 Times	21 Times	9 Hours	1 Hour	0.6 Hours



## **Specifications**

#### **General Data**

o chicrar bata	
Capacity	864Wh
Cell Туре	LiFePO <sub>4</sub>
AC + DC Input	950W Max.
Charging Temperature	0°C-40°C/32°F-104°F
Discharging Temperature	-20°C-40°C/-4°F-104°F

#### Output

Power				1,000W in total
Voltage	JP-100VAC	US-120VAC	CN-220VAC	EU/UK/AU- 230VAC
Current	10A	8.3A	4.5A	4.3A
Frequency	quency 50Hz/6			50Hz / 60Hz
UPS Switchir	ng Time			≤20ms
Cigarette Lig	hter Port *1			12VDC / 10A
USB-A *2	JSB-A*2 5VDC/			5VDC / 2.4A
USB-C *2	5 / 9 / 12 / 15 / 20VDC, 3A; 20VDC, 5A			
Wireless Cha	arging Pad *1			15W Max.
Input				

#### Input

Voltage	JP-100VAC	US-120VAC	CN-220VAC	EU/UK/AU-230VAC	
Max. Current	9A	9A	6A	6A	
Frequency				50Hz / 60Hz	
Solar Input		12~58V, 500W Max.			
Others					
Connectivity				Bluetooth	
Dimensions (L×	W×H)	314mm×209.5mm×255.8mm/12.4in×8.2in×10.1in			
Net Weight				10.7kg / 23.6lbs	

### **BLUETTI Solar Panel Recommendations**

	0		
<b>PV120</b> x 2	<b>PV200</b> x 2	<b>PV350</b> x 1	<b>PV420</b> x 1

### Pair with BLUETTI expansion battery





